

**EXPRESS MAIL CERTIFICATE**

DOCKET NO. : 201951/141

APPLICANT(S) : Jeffrey Zarnowski, Matthew Pace, Thomas Vogelsong, and  
Michael Joyner

TITLE : A VIDEO BUS FOR HIGH SPEED MULTI-RESOLUTION  
IMAGERS AND METHOD THEREOF

Certificate is attached to the **Utility Patent Application (26 pages) and  
UNSIGNED Combined Declaration and Power of Attorney (3 pages)** of the above-named  
application.


“EXPRESS MAIL” NUMBER: EL640135719US

DATE OF DEPOSIT: January 23, 2001

I hereby certify that this paper or fee is being deposited with the United States  
Postal Service “Express Mail Post Office to Addressee” service under 37 CFR 1.10 on the  
date indicated above and is addressed to the Assistant Commissioner for Patents, Box Patent  
Application, Washington, D.C. 20231.

**Gunnar G. Leinberg**

(Typed or printed name of person mailing  
paper or fee)



(Signature of person mailing paper or fee)

201951/141

**TITLE:**                   **A VIDEO BUS FOR HIGH SPEED MULTI-  
RESOLUTION IMAGERS AND METHOD THEREOF**

**INVENTORS:**           **JEFFREY ZARNOWSKI, MATTHEW PACE,  
THOMAS VOGELSONG, AND MICHAEL JOYNER**

**DOCKET NO.:**       **201951/141**

## **A VIDEO BUS FOR HIGH SPEED MULTI-RESOLUTION IMAGERS AND METHOD THEREOF**

This application is a continuation-in-part application of Application Serial  
5 No. 09/490,374 filed on January 24, 2000 which is a continuation-in-part  
application of U.S. Patent No. 6,084,229 issued on July 4, 2000.

### **FIELD OF THE INVENTION**

This invention relates generally to a bus and, more particularly, to a video  
10 bus for high speed multi-resolution imagers.

### **BACKGROUND OF THE INVENTION**

A solid state imager is a semiconductor device capable of converting an  
optical image into an electronic signal. Imagers can be arranged in a matrix and  
15 utilized to generate video signals for video cameras, still photography, or  
anywhere incident radiation needs to be quantified. When incident radiation  
interacts with a photogate, charge carriers are liberated and can be collected for  
sensing. The number of carriers collected in a photogate represents the amount of  
incident light impinging on the site in a given time-period.

20 There are two basic devices with many variants, employed to collect and  
sense, charge carriers in a photogate. The two basic devices are photodiodes and  
photogates. Variants of photodiodes include, but are not limited to: Pinned, P-I-  
N, Metal-Semiconductor, Heterojunction, and Avalanche. Photogate structures  
25 include: Charge Couple Devices (CCD), Charge Injection Devices (CID) and their  
variants that include virtual phase, buried channel and other variations that utilize  
selective dopants. The selective dopants are used to control charge collection and  
transfer underneath and between the photogate(s) and the sense node.

30 The solid state imagers heretofore used have been dominated by CCD's  
because of their low noise as compared to Photodiodes and CIDs. The low noise  
advantage of CCD imagers is the result of collecting the photon generated charge  
at the pixel site and then coupling or shifting the actual charge to an amplifier at

the periphery of the array. This eliminates the need for the long polysilicon and metal busses that degrade the signal with their associated resistance and capacitance. However, the low noise of the CCD requires the imager to be read in a fixed format and once the charge is read it is destroyed. The requirement of  
5 coupling the collected photon charge from the pixel to the periphery amplifier (a.k.a. CTE), requires proprietary processing steps not compatible with industry standards CMOS or BiCMOS processes.

Solid state imaging devices have developed in parallel with CMOS  
10 technology and as a result all imager manufacturers developed their own proprietary processes to maximize imager performance characteristics and wafer yield. Specialized silicon wafer processing kept imager prices relatively high. Linear active pixel sensors have been commercially produced since 1986. Beginning in the early 90's the move to transfer the proprietary processes to an  
15 industry standard CMOS processes was on. The advantages of using an industry standard process include: competitive wafer processing pricing, and the ability to provide on chip timing, control and processing electronics. By the end of the year 1992, a 612 x 512 CMOS compatible, CID imager with a preamplifier and CDS per column had been fabricated. The imager could either be operated as a random  
20 access 512 x 512 CID, or all the columns could be summed together and operated as a linear active pixel sensor.

Area arrays utilizing active pixel sensors in which a photodiode or photogate is coupled to an output source follower amplifier which in turn drives a  
25 Correlated Double Sampling (CDS) circuit, where the two outputs of the CDS cell then drives two more source followers circuits that in turn are fed into a differential amplifier are shown in U.S. Patent No. 5,471,515 which is herein incorporated by reference. This uses source follower circuits, that typically have gains less than unity that vary from one source follower to another. The source  
30 follower gain variation is due to variations of FET thresholds. The source follower gain variation results in a pixel to pixel gain mismatch. Also, the active pixel sensors suffer gain variations due to the CDS circuit per column, when the CDS employs a source follower pair to drive its output. The resulting CDS signal

and its corresponding offset can have different gains that are not correctable by the differential amplifier. Also, the source follower configuration of active pixel doesn't allow for binning of pixels.

5           The voltage mode of operation of prior art does not allow for binning, which, is the summation to two or more pixel signals at once.

What is needed is an imager which has the low noise level of a CCD, the random access, and binning of a CID, and uniform gain and response from all  
10       pixels; while, maintaining low power, ease of use and high analog video frame rates.

In addition to finding an imager which has the low noise level of a CCD, the random access, and binning of a CID, and uniform gain and response from all  
15       pixels, imagers suitable for industrial and/or scientific applications are also needed. Over the last 30 years the CCD sensor and camera electronics technology has evolved to meet most of the demands for industrial and/or scientific applications. However, the resulting cameras require a state-of-the-art, large pixel, multi-port CCD chip plus several extra chips and usually several circuit  
20       boards filled with electronics to accomplish this. Thus, the cameras cannot physically fit in certain applications, the power consumed is significant, and the resulting cameras are far too expensive for many applications. The necessary recombination of the video data from several ports, further increases the video processing complexity and ultimately drives-up the cost and size of the video  
25       system.

As discussed earlier over the past several years, thanks to design rule shrinkage, image sensors using sub-micron CMOS process technology have become practical. By using CMOS technology for the sensor array itself, the  
30       problem of integrating extra circuitry on chip becomes straightforward. Elements such as A/D converters, timing generators, control circuitry and interface circuitry can easily be added. In addition, the operation of CMOS imagers is simplified by the elimination of the need for precise timing and level control of multiple clocks

required to drive the large capacitance transfer gates inherent in CCD's. Even with all of these factors, including the exceptional speed and pico-second gate delays of sub-micron processes, the analog video bandwidth per port has not changed much over the past twenty years.

5

Active pixel sensors (APS) have been proposed as the means to achieve the flexible benefits of CMOS cameras on a chip. Unfortunately, there are performance issues with the fundamental APS approach that limit its performance and functionality. While these limitations may be acceptable for low-end consumer imaging applications, the demands of scientific, professional and industrial applications have, up until now, been largely unmet by CMOS image sensors.

10

More specifically, industrial and scientific imaging applications require much higher performance and functionality than that required for low-end consumer imaging products. Many of the applications require high readout speeds for video rate or even faster imaging without sacrificing image quality. In addition to image quality, the applications have come to demand greater functionality in the camera. Features such as flexible shuttering and electronic zoom, random access and selectable region of interest for maximizing frame rates and minimizing data storage (especially useful in tracking applications). Lowering the cost of machine system development is the recent advancement of single chip CMOS cameras. Newly developed CMOS cameras have all the flexibility previously listed, however the analog video bandwidth per port has not changed from the traditional CCD, CID or Photodiode technologies.

15

20

25

30

Most mega-pixel image sensors, including both CCD imagers and APS imagers, have a maximum pixel rate inadequate to meet the frame rate needs of industrial and scientific imaging. CCD devices are limited by both clocking rates and the speeds of the Correlated Double Sampled (CDS) circuitry. In addition the higher amplifier bandwidth required for higher pixel rates increases noise levels. With the column parallel nature of CMOS imagers, the amplifier and CDS can be run at the line rate rather than the pixel rate. The video bandwidth constraints

come in terms of the multiplexing speed. CMOS imagers typically multiplex their signals onto a common analog video bus. The more signals that are multiplexed or switched onto the bus, the greater the capacitive load of that bus. Therefore, as more signals are connected to the bus, the bandwidth of the bus is reduced.

5 Alternatively, greater power is needed to charge and discharge the bus with its associated capacitance to maintain bandwidth. This traditional bus structure described above involves N signals that are switched onto one bus.

One example of a CMOS imager 98 with column parallel amplifiers 100  
10 that drive a common video bus 102 is illustrated in Figure 5. In this example, the common video bus 102 is seen mostly as a capacitive load 140 to each individual column amplifier 100. In order for each amplifier 100 to truly represent the pixel value onto the common video bus 102, each amplifier 100 must charge or  
15 discharge the bus 102 within one pixel time constant. The pixel value signal must be stable long enough for a sample and hold circuit (or similar) to accurately present the resultant signal to an A to D converter (not shown). Typically, at least  $5\tau$  (tau or time constants) is desired to accurately allow the video bus 102 to settle the video value presented by each individual column amplifier 100, although this can vary between applications. At higher video bus speeds each amplifier 100 is  
20 unable to properly charge or discharge the video bus 102 resulting in a loss of contrast ratio. At higher pixel element rates where the contrast ratio is compromised, the individual column amplifier characteristic and the video switch characteristics begin to affect the resultant video. Each individual column amplifiers 140 has a slightly different offsets with slightly different drive  
25 capabilities and each video switch 120 will have slightly different resistances and slightly different thresholds. This combination of column amplifier and video switch characteristics results in each column amplifier 100 having different time constants relative to charging and discharging the video bus 102. The column amplifier 100 and video switch 120 are common to every pixel in that column.  
30 Thus, variations in the video switch characteristics result in what appears to be column based Fixed Pattern Noise (FPN). As more columns are added, each video switch 120 adds more associated capacitance 140 due to the source and

drain junctions of MOSFET or Bipolar transistors. The more columns added to the bus 102, the higher the total capacitance.

In order to overcome these constraints, one prior solution by designers of  
5 CCD's and APS sensors has been to divide up the imager into halves, quarters, or  
smaller groupings of sub-imagers jammed together. One example of this prior  
design solution is shown in Figure 6. In this example, the imager 80 is divided up  
it to four sub-imagers 80(1)-80(4). The signal from each of these sub-imagers  
80(1)-80(4) is brought out to its own port 82(1)-82(4). This structure or  
10 architecture also involves getting many signal streams of N signals on to one bus.  
This design has been used to provide high frame rate devices and to meet standard  
frame rates with large mega-pixel imagers. Unfortunately, this design adds  
system size, complexity, power and cost to handle the multiple analog amplifier  
chains. Additionally, it is an extremely challenging task to balance the amplifier  
15 chains completely over all possible pixel rates and temperatures. This issue has  
become even more of a problem in recent years as imagers have grown larger,  
now up to full wafer size. The process variations across an array can lead to  
further balance problems, and even variations in noise characteristics due to  
process variations across a wafer.

20

### **SUMMARY OF THE INVENTION**

A bus system for transferring signals from a plurality of signal streams to  
an output in accordance with one embodiment of the present invention includes a  
plurality of signal buses in parallel and a control system. The control system  
25 multiplexes the signals from two or more of the plurality of signal streams onto  
two or more of the plurality of signal buses and allows the signals to substantially  
charge each of the two or more of the plurality of signal buses before selecting the  
signals to the output multiplexor.

30

An imager in accordance with another embodiment of the present  
invention includes a plurality of streams of signals, a plurality of signal buses in  
parallel, an output, and a control system. The control system multiplexes the  
signals from two or more of the plurality of signal streams onto two or more of the



plurality of signal buses ( i.e. an input multiplexor) and allows the signals to substantially charge each of the two or more of the plurality of signal buses before demultiplexing the signals to the output multiplexor.

5           A bus system for transferring signals from a plurality of signal streams to an output in accordance with another embodiment of the present invention includes a plurality of signal buses coupled to the plurality signal streams, a plurality of first switches, a plurality of second switches, and a control system. Each of the plurality of first switches is coupled between one of the plurality of  
10 signal streams and one of the plurality of signal buses. Each of the plurality of second switches coupled between one of the plurality of signal buses and the output. The control system is coupled to the first and second switches and closes two or more of the plurality of first switches to couple signals from the two or more of the plurality of signal streams to two or more of the plurality of signal  
15 buses and allows the signals to substantially charge each of the two or more of the plurality of signal buses before closing one or more of the plurality of second switches of the output multiplexor to couple the signals to the output. In other words, this system described above involves N signals multiplexed to two or more busses (or M busses) and then multiplexed on to one bus or in other words a  
20 two stage multiplexor with an input multiplexor and an output multiplexor. A two stage multiplexing system allows for a variety of different operations, such as allowing signal or pixel signal skipping and allowing multiple signals or pixels signals to be selected at once. By way of example, pixel signals could be alternately individually selected and then two adjacent signals could be selected to  
25 allow signal averaging or interpolation, effectively changing the native resolution of pixel for either higher or lower resolution. This present invention coupled with Active Column Technology as described in U.S. Patent Number 6,084,229, which is herein incorporated by reference, allows for binning or skipping of pixels along the rows as well as the columns.

30           A method for transferring signals in accordance with yet another embodiment of the present invention includes multiplexing signals on to two or more of a plurality of signal buses and allowing the signals to substantially charge

each of the two or more of the plurality of signal buses also known as input multiplexing before demultiplexing select signals by the output multiplexor. Also, included in this particular embodiment is a reordering multiplexor that redirects signals from the output multiplexor to one or more outputs.

5

#### **BRIEF DESCRIPTION OF THE DRAWINGS**

Figure 1 is a prior art double polysilicon active pixel sensor;

Figure 2 is an active column sensor in accordance with this invention;

Figure 3 is an implementation of a pixel in accordance with the invention;

10

Figure 4 is a schematic illustration of a matrix of pixels connected to incorporate a full operational amplifier per pixel forming an Active Column Sensor;

Figure 5 is a view of a conventional method of driving a common video bus on an imager;

15

Figure 6 is a view of a traditional CCD and CMOS sensor method of increasing video bandwidth with multiple ports;

Figure 7A is a diagram of an imager with a high speed, low noise bus system in accordance with one embodiment of the present invention;

20

Figure 7B is an enlarged view of a decoder and a preselection circuit in the imager shown in Figure 7A;

Figure 7C is an enlarged view of an address counter and control circuit in the image shown in Figure 7A;

25

Figure 8A is a diagram of an imager with a bus system for pixel interpolation for increased resolution in accordance with another embodiment of the present invention;

Figure 8B is an enlarged view of an address counter and a control circuit in the imager shown in Figure 8A; and

30

Figure 9 is a block diagram of a bus system with another bus output multiplexor, control circuit, and video processing block in accordance with another embodiment of the present invention.

## DETAILED DESCRIPTION

Before discussing the Active Column Sensor (ACS) circuit of Figure 2 of the present invention and described in conjunction with a discussion of ACS below, it will be useful to discuss the structure of a typical double-polysilicon active pixel sensor of prior art as shown in Figure 1.

In Figure 1 each pixel 50 has a photogate 60 that has an output FET 53 configured as a source follower. The source follower 53 is used to drive a subsequent signal conditioning circuitry, such as a Correlated Double Sampled Circuit (CDS) 55. The gain through a source follower 53 is less than unity. If the source follower located at the pixel site 50 has a given gain other pixels and their respective source followers in the same column may or may not have the same gain. The technique relies on wafer processing for all FETs in the array to have the same threshold. It isn't uncommon for FET thresholds, during operation, to vary by 100mV for a linear active pixel array.

The active pixel 50 of the prior art includes a photogate 60 and a transfer gate 62 that are used to couple photo generated charge onto the floating diffusion node 52 which is connected to the gate 56 of source follower 53. The drain of the output FET 53 is connected directly to a power supply rail VDD. The source follower output FET is in turn connected to the source 57 of row access FET 58. When the row access FET 58 is selected for reading, the FET 58 is turned on, allowing output FET 53 to be connected to a load 18 and drive the CDS circuitry 55 directly.

25

Figure 2 is a schematic diagram of a pixel 12 in accordance with the present invention in which the threshold variations from pixel to pixel of the prior art are eliminated. All pixels 12 in a row or column are in parallel and for simplicity only one is shown. Pixel 12 which can consist of any photosensitive device 10 is coupled to a FET 15 to isolate the pixel from the readout circuitry. The FET 15 is one FET of a differential input pair of an operational amplifier 30 that includes FET 24. For simplicity, in Figure 2 the amplifier circuit 30 is configured as a positive feedback unity gain amplifier. A feedback path 32

30

connects the output of amplifier 30 to input 17 which in this case is the gate of FET 24. The amplifier 30 could be configured to have gain, a full differential input or any operational amplifier configuration as the application required. The fixed gain of amplifier 30 eliminates the gain variability of the prior art. The  
5 output of the unity gain amplifier is connected to a Correlated Double Sampler (CDS) which is utilized to eliminate any fixed pattern noise in the video.

A current source 20 comprising an FET 22 has its source connected to a power source VDD and its drain connected to the sources of differential input  
10 FETs 15 and 24.

The drains of input FETs 15 and 24 are connected to a current mirror formed from FETs 26 and 28. The gates of FETs 26 and 28 are connected together and to the source 18 of input FET 15. The sources of FETs 26 and 28 are  
15 connected to a negative power source, VCC.

The drain 30 of FET 24 is the output of the differential pair and is connected to CDS 34.

The input FET 15 could be either a N channel or P channel FET as the  
20 application requires. The pixel 80 could be either a photogate or photodiode.

Figure 3 is a detailed schematic of pixel 12 of the active column sensor shown in Figure 2. In this implementation a photogate 76 is utilized. Selection  
25 and reset of a sense node 72 is controlled by an FET 76. This Active Column Sensor pixel eliminates the separate selection/access FET 58 of prior art. All biasing and controls signals are supplied from the periphery of the pixel array.

The pixel can be operated in the following manner. An N type substrate is  
30 used and the substrate is biased the most positive potential, e.g. 5.0 volts. The photogate 70 preferably a layer of polysilicon is biased to an integrate level (e.g. 0.0 volts). The region 80 under the photogate 70 is depleted and as light strikes the immediate area, it will collect (integrate) photon generated carriers.

Photogate 72 is biased to the 5.0 volts and will not collect photon generated carriers during the integration because it is biased to the same potential as the substrate. Photogate 72 is biased by selecting control FET 76 with the reset/Select Control signal. In this configuration control FET 76 is a P channel FET that is  
5 selected by a negative signal relative to the substrate, for example 0.0 volts. During integration FET 76 is selected, the photogate is biased by the reset/select bias that preferably is at 5.0 volts. After a predetermined integration time period the pixel is read.

10 Reading the pixel is preferably accomplished in the following manner. The reset/select control is changed to 2.5 volts, causing the region beneath photogate 72 to be depleted, and the background level is read. Reset/select FET 76 is turned off by setting the reset/select control to 5.0 volts. Photogate 70 has its potential removed, and in this example 5.00 volts. Reading the signal will occur  
15 as the collected photon generated charge transfers from the region beneath photogate 70 to the region beneath photogate 72. The transferred photon generated charge modulates the gate of input FET 15, according to the amount of collected.

20 Fixed Pattern Noise (FPN) can be eliminated from the video information by utilizing CDS circuit 34. The first sample applied to the CDS circuit is the background level. The signal information is then applied to the CDS. The difference of the two signals provides for a fixed pattern noise free signal.

25 Figure 4 is a schematic diagram of an array of pixels in accordance with this invention. A plurality of pixels 90a, 90b, 90c form a first column of the array, and similar columns 92a-c and 94a-c complete the array. Within each column, the pixels are connected with their output FETs in parallel, the combination forming the first one of the differential input pair of operational amplifier 30. In all other  
30 respects, amplifiers 30a, 30b and 30c are identical to Figure 2. Each amplifier 30 is connected to a CDS 34a, 34b, and 34c respectively. The outputs of CDS 34a, b, c are connected through column select switches 96a, 96b, and 96c, the common terminals of which are connected to output buffer 98 which can be a source

follower, or a more complex signal conditioner as required by the specific application.

As discussed earlier, industrial and scientific imaging applications require much higher performance and functionality than that typically required for consumer imaging products. More specifically, many of these applications require high readout speeds for video rate or even faster imaging without any sacrifice in image quality. One of the advantages of the present invention is that it provides an on-board, high-speed bus system 200 or PVS bus that allows pixel rates exceeding those of prior single port CCD or APS devices and other prior analog buses. This bus system 200 in combination with the highly parallel nature of amplifier per column techniques of CMOS sensors provides the functionality and the high speed performance required for scientific and industrial applications. This speed increase has been achieved without increasing power consumption while maintaining full video bandwidth even at the higher speeds. Additionally, the present invention is able to eliminate common mode noise pickup through the use of fully differential processing. Further, the high speed, low noise, low power, analog PVS bus utilizes either standard sequential or random access decoders for selection of a particular column. In addition to selecting a column, the bus system 200 has the added preselection circuitry to pre-select the next multiple columns in the read sequence in parallel. The number of columns pre-selected can be scaled to meet the application requirements.

Referring more specifically to Figure 7A, a diagram of an imager 202(1) with a high speed, low noise bus system 200(1) in accordance with one embodiment of the present invention is illustrated, although the bus system 200 could be used with a variety of different types of devices, such as video cross point switch, and for a variety of different types of applications. In this particular embodiment, the imager 202(1) includes a pixel array 204 with a plurality of columns 206(1)-206(n) and rows 208(1)-208(n) of pixels along with image processing circuitry, such as that described earlier with reference to Figures 2-4. An optional correlated double sampling ("CDS") circuit 210 is coupled to the end of each of the columns 206(1)-206(n) in this example. Although in this particular

example the bus system 200(1) is coupled to the end of the columns 206(1)-206(n) for the array 204, the bus system 200(1) could also be coupled in to other locations, such as to the end of the rows 208(1)-208(n) of the array 204.

5           A multiplexor 212 is coupled to one of the ends of the columns 206(1)-206(n) for the array 204, although the multiplexor 212 could be coupled to other locations and to other sources of data. In this particular embodiment, the multiplexor 212 comprises a plurality of multiplexing buses 214(1)-214(4) and 216(1)-216(4), a plurality of switches 218(1)-218(8), and a preselection or control  
10       circuit 220, although the multiplexor 212 could be made of other components. The multiplexor 212 selects multiple columns 206(1)-206(n) or rows 208(1)-208(n) of the array 204 and then multiplexes signals from those columns 206(1)-206(n) or rows 208(1)-208(n) on to the multiplexing buses 214(1)-214(4) and 216(1)-216(4) at the same time.

15           More specifically, in this particular embodiment each column 206(1)-206(n) of the array 204 through the CDS circuit 210 is coupled to one of the plurality of multiplexing buses 214(1)-214(4) and 216(1)-216(4). There are four pairs of multiplexing buses: 214(1), 216(1); 214(2), 216(2); 214(3), 216(3); and  
20       214(4), 216(4), with one pair of multiplexing video buses coupled to each column of the array 206(1)-206(4), although the total number and types of buses as well as the number of buses coupled to each column or row of the array 204 can vary as needed or desired. In this particular embodiment, a pair of multiplexing buses are coupled to each column of the array to permit differential processing.

25           The switches 218(1)-218(8) are each coupled between one of the columns 206(1)-206(4) of the array 204 and one of the multiplexing buses 214(1)-214(4) and 216(1)-216(4). Each of the switches 218(1)-218(8) has an open position and a closed position. In an open position, the switches 218(1)-218(8)  
30       disconnect the columns 206(1)-206(4) of the array 204 from the multiplexing bus 214(1)-214(4) and 216(1)-216(4) and in a closed position the switches 218(1)-218(8) couple the columns 206(1)-206(4) of the array 204 to the multiplexing buses 214(1)-214(4) and 216(1)-216(4).

The preselection circuit 220 (also shown in Figure 7B) is coupled to each of the switches 218(1)-218(8) and controls whether each of the switches 218(1)-218(8) is in an open or a closed position. Since control circuits to control the opening and closing of switches are well known to those of ordinary skill in the art, the preselection circuit 220 will not be described in detail here. In this particular embodiment, the preselection circuit 220 comprises a plurality of "OR" Boolean logic function gates ("OR gate") 222(1)-222(n) that each have four inputs and one output, although other types of components with other numbers of inputs and outputs and other types of logic functions could be used for the preselection circuit 220.

A decoder 224 (also shown in Figure 7B) with a plurality of inputs and a plurality of outputs is coupled to the preselection circuit 220. A variety of different types of decoders 224 could be used, such as a sequential decoder or a random decoder. The decoder 224 transmits input signals to each of the OR gates 222(1)-222(n). The output of each OR gate 222(1)-222(n) is coupled to one of the switches 218(1)-218(n) and depending upon the signals received via the inputs to the OR gates 222(1)-222(n), the signal from the output of the OR gate 222(1)-222(n) coupled to each switch 218(1)-218(n) will either open or close that switch 218(1)-218(n). In this particular embodiment, the decoder 224 and preselection circuit are designed to couple multiple columns of the pixel array to the different multiplexing buses 214(1)-214(4) and 216(1)-216(4) at one time.

An output multiplexor 226 is coupled to each of the multiplexing buses 214(1)-214(4) and 216(1)-216(4) and is designed to match the configuration of the multiplexor 212. In this particular embodiment, the output multiplexor 226(1) comprises the plurality of multiplexing buses 214(1)-214(4) and 216(1)-216(4), a plurality of switches 228(1)-228(8), and a control circuit 230(1), although the output multiplexor 226 could be constructed of other components. The switches 228(1)-228(n) remain closed at least until the signal(s) from the columns 206(1)-206(n) have changed the bus(es) 214(1)-214(4) and 216(1)-216(4) in this particular example. The timing for the output multiplexor 226 is generated via



external control (not shown), such as an on chip counter, a small shift register, or a controller.

In this particular embodiment, the control circuit 230(1) (also shown in  
5 Figure 7C) comprises a plurality of AND gates 232(1)-232(4) which each have a pair of inputs and an output, although other types of components with other numbers of inputs and outputs and other types of logic functions could be used for the control circuit 230. An address counter 234 transmits input signals to each of the AND gates 232(1)-232(4). The output of each AND gate 232(1)-232(4) is  
10 coupled to one of the switches 228(1)-228(8) and depending upon the signals received via the inputs to the AND gates 232(1)-232(4), the signal from the output of the AND gates 232(1)-232(4) will either open or close the switches 228(1)-228(8) coupled to the AND gates 232(1)-232(4). In this example, the control circuit 230(1) is used to select the signal from one column 206(1), 206(2), 206(3),  
15 or 206(4) of the pixel array 204 at a time, although the control circuit 230(1) can be configured with other components and controlled with other input signals to select one or more signals from one or more other columns 206(1)-206(4) of the pixel array 204 at a time.

20 In this particular embodiment, a video processing circuit 236 is coupled to the output of the output multiplexor 226, although other types of processing circuits can also be used. The video processing circuit 236 takes the differential video from the two buses: 214(1), 216(1); 214(2), 216(2); 214(3), 216(3); and 214(4), 216(4), coupled to the video processing circuit 236 and provides gain,  
25 offset, filtering, and/or any other desired processing function in manners well known to those of ordinary skill in the art.

Referring to Figures 8A, an imager 202(2) with a high speed, low noise bus system 200(2) in accordance with another embodiment of the present invention is  
30 illustrated. Figures 8A and 8B illustrate how this particular embodiment can be utilized to change the native resolution of an imager. Since the imager 202(2) and bus system 200(2) in Figure 8A is the same as the imager 202(1) and bus system 200(1) in Figure 7A except for the control circuit 230(2), only the control circuit

230(2) of Figures 8A and 8B will be described here. In Figures 8A and 8B the control circuit 230(2) comprises an address counter 234 with a plurality of inputs and a plurality of outputs along with a plurality of AND gates 238(1)-238(4) and 240(1)-240(4) and OR gates 242(1)-242(4) and 244(1)-244(4) which each have a pair of inputs and an output. Node 5 is connected to itself. Since control circuits to control the opening and closing of switches are well known to those of ordinary skill in the art, the control circuit 230(2) will not be described in detail here. In this particular embodiment, the control circuit 230(2) with the address counter 234, and interpolation control signal 243, is configured to interpolate the signals from the columns 206(1)-206(n) of the pixel array 204 as explained in greater detail later. In this example, the address counter 234 transmits input signals to the control circuit 230(2). The control circuit 230(2) is coupled to the switches 228(1)-228(8) and depending upon the signals received at the inputs to the control circuit 230(2), the signals from the control circuit 230(2) will either open or close the switches 228(1)-228(8) to provide column interpolation in this example.

Referring to Figures 7A-7C, by pre-selecting the three columns ahead of time, the column processing circuitry only has to drive the multiplexing buses 214(1)-214(4) and 216(1)-216(4) at one quarter the actual pixel read rate (one-fourth the bandwidth). Only the demultiplexing in is done at the normal bandwidth. Thus, the column processing circuit, such as the active column sensor technology described in Figures 2-4, can be made smaller and requires less power than it would otherwise have to be. Also, since only one out of every four columns 206 of the pixel array 204 is coupled to each multiplexing bus in this example, each of the multiplexing buses 214(1)-214(4) and 216(1)-216(4) has only one-fourth of the capacitance, because there are only one fourth of the switches or transmission gates to drive. Further, with the present invention the column selection sequence remains conventional, without the need for post processing reconstruction of the original image as is required of multi-port imagers, such as the one shown in Figure 6.

Another useful approach to the column parallel nature of the imager 202(1) with the bus system 200(1) in accordance with the present

invention is the ability to select multiple columns at once to average the video signal. This is possible because the column amplifiers in the processing circuitry for the pixel array 204 are identical in every detail and when more than one is selected at once, the outputs from each amplifier try to drive each other and the result is that the two or more signals are averaged. This allows for higher speed of operation and it also gives a new method of binning or interpolating pixels. Binning is a term used to combine two or more pixel signals together. The higher speed of operation is due to two or more amplifiers driving the same video bus and as a result there is up to two times (or more) the ability to drive the same amount of capacitance. The binning is a result of combining two or more signals at the same time on the same bus 214 or 216. The control circuit 230(1) in the output multiplexor 226(1) can be configured and controlled with signals to couple two pairs of multiplexing buses: 214(1), 216(1); 214(2), 216(2); 214(3), 216(3); and 214(4), 216(4) to the video processing circuit 236 at one time for binning.

This multi-resolution ability of the bus system 200(1) can also be used to effectively increase the resolution through interpolation, not just decrease the resolution through binning as shown in Figures 8A and 8B. The imager 202(2) with the bus system 200(2) in Figures 8A and 8B operates in the same manner as the imager 202(1) with the bus system 200(1) in Figures 7A-7C, except that with the control circuit 230(2) in Figures 8A and 8B column interpolation is possible. In this embodiment, the increase of resolution is through the use of selectively binning adjacent signals in between reading individual signals with the control circuit 230(2). In this manner, the time sequence would be select the multiplexing buses 214(1) and 216(1) coupled to column 206(1) for coupling via closing switches 228(1) and 228(2) to the video processing circuit 236 and read the signal. Next in sequence leave column 206(1) selected and also select the multiplexing buses 214(2) and 216(2) coupled to column 206(2) via closing switches 228(3) and 228(4) for coupling to the video processing circuit 236. Read the combined (binned or averaged) signal and deselect column 206(1) by opening switches 228(1) and 228(2) to disconnect the multiplexing buses 214(1) and 216(1) coupled to column 206(1) from the video processing circuit 236 and only read the signal from the multiplexing buses 214(2) and 216(2) coupled to column 206(2). In this

manner for every two adjacent signals read, a third interpolated signal can be read effectively increasing the resolution through interpolation. By way of example, an imager with a pixel array having 640 columns would have the effective resolution of 1279 pixels through interpolation or an imager with a pixel array having 480 rows would have an interpolated resolution of 969 rows. In either case, for binning or interpolation the column or row averaging is done by the output multiplexor.

Referring to Figure 9, a bus system 329 with another output multiplexor, control circuit, and video processing block in accordance with another embodiment of the present invention. This bus system 200(3) in Figure 9 is the same as either the bus system 200(1) shown in Figures 7A-7C or the bus system 200(2) shown in Figures 8A and 8B, except that this bus system 200(3) also has a reordering multiplexor circuit 330. The reordering circuit 330, is coupled to the output multiplexor circuit 226 of Figure 9, and is identical in function to the output multiplexer circuit of Figure 8A. One possible implementation of the reordering circuit 330 is shown in more detail in Figure 9. More specifically, in this particular embodiment the reordering circuit 330 is made up of switches implemented as illustrated using transmission gates 332(1-6). The signals provided by the output multiplexer on nodes 226 and 227 can be controlled to be switched to one or more of the video processing block circuits 343(1-3) by the pixel ordering logic device 342. The details of the ordering logic device 342 are not shown here, but would be obvious to one of ordinary skill in the art. The particular implementation of ordering logic device 342 would depend on the specific application and the desired reordering of signals. The function of the control logic provided by the ordering logic device 342 in combination with the reordering multiplexor circuit 330 is to redirect a signal to one or more locations. As signals on nodes 227 and 229 of Figure 9 can be redirected to one or more of the video amplifiers 342(1-3) of the video processing block 340.

Differential signals are shown on figures 7A, 7B, 7C, 8A, 8B, and 9 which can be described as a signal and a reference signal that are utilized for noise

immunity. A single ended configuration or multiple input, output and reording buses could be utilized for an application as well.

Having thus described the basic concept of the invention, it will be rather  
5 apparent to those skilled in the art that the foregoing detailed disclosure is  
intended to be presented by way of example only, and is not limiting. Various  
alterations, improvements, and modifications will occur and are intended to those  
skilled in the art, though not expressly stated herein. These alterations,  
improvements, and modifications are intended to be suggested hereby, and are  
10 within the spirit and scope of the invention. Accordingly, the invention is limited  
only by the following claims and equivalents thereto.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
22